

Propane Powered Generator Consumption Chart



Generator Size	10 KW	14 KW	17 KW	20 KW	25 KW	30 KW	36 KW	45 KW
Gallons Used Per Hour	1.93	2.3	2.57	2.9	4.3	5.1	5.3	8

Maximum Hours**

Tank Size* Gallons	10 KW	14 KW	17 KW	20 KW	25 KW	30 KW	36 KW	45 KW
120	50	41	37	33	22	19	17	12
240	100	82	74	66	44	38	34	24
250	103	87	78	70	47	40	36	25
320	132	111	99	88	60	50	46	32
360	150	123	116	99	66	57	51	36
480	200	164	150	132	88	76	68	48
500	206	174	155	137	93	78	72	50
1000	412	348	311	275	186	156	144	100

*Tanks are filled to 80% capacity to allow for expansion.

**Example: 120 gal tank X 80% = 100 gal. 100 gal / 1.93 gph = 51.8 gal. 51.8 gal / 24 hr = 2 days

***Example: Gauge reads 40%. 120 gal tank X 40% = 48 gal. 48 gal / 1.93 gph = 24.9 gal / 24 hr = 1 day